



NRL/MR/6750--04-8814

# **Preliminary Composite Channel Model for the Mobile User Objective System Including Ionospheric Scintillation and Terrestrial Multipath Effects**

MICHAEL J. KESKINEN

*Charged Particle Physics Branch  
Plasma Physics Division*

PER A. KULLSTAM

*Paircom, Inc.  
Springfield, VA*

September 20, 2004

Approved for public release; distribution is unlimited.

# REPORT DOCUMENTATION PAGE

Form Approved  
OMB No. 0704-0188

Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing this collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden to Department of Defense, Washington Headquarters Services, Directorate for Information Operations and Reports (0704-0188), 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302. Respondents should be aware that notwithstanding any other provision of law, no person shall be subject to any penalty for failing to comply with a collection of information if it does not display a currently valid OMB control number. PLEASE DO NOT RETURN YOUR FORM TO THE ABOVE ADDRESS.

<b>1. REPORT DATE (DD-MM-YYYY)</b> 20-09-2004		<b>2. REPORT TYPE</b> Memorandum		<b>3. DATES COVERED (From - To)</b>	
<b>4. TITLE AND SUBTITLE</b>  Preliminary Composite Channel Model for the Mobile User Objective System Including Ionospheric Scintillation and Terrestrial Multipath Effects				<b>5a. CONTRACT NUMBER</b>	
				<b>5b. GRANT NUMBER</b>	
				<b>5c. PROGRAM ELEMENT NUMBER</b>	
<b>6. AUTHOR(S)</b>  Michael J. Keskinen and Per A. Kullstam*				<b>5d. PROJECT NUMBER</b> 67-7930-04	
				<b>5e. TASK NUMBER</b>	
				<b>5f. WORK UNIT NUMBER</b>	
<b>7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES)</b>  Naval Research Laboratory, Code 6750 4555 Overlook Avenue, SW Washington, DC 20375-5320  Paircom, Inc. Springfield, VA 22153				<b>8. PERFORMING ORGANIZATION REPORT NUMBER</b>  NRL/MR/6750--04-8814	
<b>9. SPONSORING / MONITORING AGENCY NAME(S) AND ADDRESS(ES)</b>  Space and Naval Warfare Systems Command Communications Satellite Programs PMW-146 Attn: Mr. Pat Browne 4301 Pacific Highway San Diego, CA 92110-3127				<b>10. SPONSOR / MONITOR'S ACRONYM(S)</b>	
				<b>11. SPONSOR / MONITOR'S REPORT NUMBER(S)</b>	
<b>12. DISTRIBUTION / AVAILABILITY STATEMENT</b>  Approved for public release; distribution is unlimited.					
<b>13. SUPPLEMENTARY NOTES</b>  *Paircom, Inc., Springfield, VA 22153					
<b>14. ABSTRACT</b>  A composite channel model, which combines ionospheric scintillation fading and terrestrial multipath effects, has been developed for the new satellite communications system, the Mobile User Objective System (MUOS). We numerically solve the composite model and compute an effective decorrelation time and coherence bandwidth for the composite channel. We find that, under typical conditions, the effective channel decorrelation time and coherence bandwidth can be different from the ionospheric or terrestrial channel parameters.					
<b>15. SUBJECT TERMS</b>  Satellite communications; Ionosphere; Scintillations					
<b>16. SECURITY CLASSIFICATION OF:</b>			<b>17. LIMITATION OF ABSTRACT</b>	<b>18. NUMBER OF PAGES</b>	<b>19a. NAME OF RESPONSIBLE PERSON</b>
<b>a. REPORT</b> Unclassified	<b>b. ABSTRACT</b> Unclassified	<b>c. THIS PAGE</b> Unclassified	UL	9	Michael J. Keskinen
					<b>19b. TELEPHONE NUMBER (include area code)</b> (202) 767-3215

20041008 287

# **PRELIMINARY COMPOSITE CHANNEL MODEL FOR THE MOBILE USER OBJECTIVE SYSTEM INCLUDING IONOSPHERIC SCINTILLATION AND TERRESTRIAL MULTIPATH EFFECTS**

M. J. Keskinen  
Charged Particle Physics Branch  
Plasma Physics Division  
Code 6750  
Naval Research Laboratory  
Washington, DC 20375

Per A. Kullstam  
Paircom, Inc.  
Springfield, VA 22153

## **ABSTRACT**

A composite channel model, which combines ionospheric scintillation fading and terrestrial multipath effects, has been developed for the new satellite communications system, the Mobile User Objective System (MUOS). We numerically solve the composite model and compute an effective decorrelation time and coherence bandwidth for the composite channel. We find that, under typical conditions, the effective channel decorrelation time and coherence bandwidth can be different from the ionospheric or terrestrial channel parameters.

## **INTRODUCTION**

The Mobile User Objective System (MUOS) will provide satellite communications for a wide range of operational environments and for a large class of user terminals. The typical MUOS operational environments can be classified as land, ocean,

and aeronautical-mobile satellite communications channels. Each of these channels has propagation conditions ranging from benign to stressed. For example, due to ionospheric effects, MUOS signal transmissions can suffer both amplitude and phase scintillation and associated fading at both low and high latitudes depending on geomagnetic conditions. Strong ionospheric scintillation can also occur at UHF during magnetic storms at mid latitudes over the continental United States. In addition, in terrestrial environments, e.g., urban, suburban, maritime, strong multipath can also lead to signal fading. In the past ionospheric scintillation and terrestrial multipath fading have been studied separately. Some initial efforts have been made to develop a composite model [1-5]. A composite model is important for waveform design, signal demodulation, and fading mitigation. However a quantitative composite model has not been developed to date. In this preliminary study we develop a coupled model for the combined effects of ionospheric scintillation and terrestrial multipath. We then numerically solve the model for channel parameters for an urban multipath environment undergoing ionospheric scintillation.

## MODEL

For the Rician ionospheric scintillation channel we take the following expression for the signal auto-correlation function [1]

$$\begin{aligned} R_1(\tau, \Delta f) &= S_0[p + q\rho(\tau, \Delta f)]\exp(i2\pi\delta f\tau) && \text{Rician} \\ &= S_0\rho(\tau, \Delta f)\exp(i2\pi\delta f\tau) && \text{Rayleigh} \end{aligned} \quad (1)$$

where  $S_0 = R_1(\tau=0, \Delta f=0)$  is the total signal power,  $pS_0 = S_s$  is the specular power and  $qS_0 = S_r$  is the random or Rayleigh power,  $\rho(\tau, \Delta f)$  is the normalized ionospheric scintillation auto-correlation function for the Rayleigh portion, and  $\delta f$  is the Doppler frequency shift for a moving mobile platform. If  $p = 0$  ( $q = 1$ )  $S_s = 0$  and  $S_r = S_0$  and we have Rayleigh fading. The general expression for the signal auto-correlation function [1,3]

$$R(\tau, \Delta f) = \langle E(t+\tau, f+\Delta f)E^*(t, f) \rangle \quad (2)$$

where  $E$  is the complex envelope representation of the signal with  $*$  denoting complex conjugate and  $\langle . \rangle$  the expectation operator. For the Rayleigh scintillation channel

without terminal Doppler we have the normalized auto-correlation function [1,2]

$$\begin{aligned} \rho(\tau, \Delta f) &= R(\tau, \Delta f)/R(0,0) & R(0,0) &= R(\tau=0, \Delta f=0) & (3) \\ &= \exp[-(\tau/\tau_{01})^2/(1+i\Delta f/f_{01})/(1+i\Delta f/f_{01})] & & \text{Rayleigh} \end{aligned}$$

where  $\tau_{01}$  is the signal decorrelation time and  $f_{01}$  is the channel coherence bandwidth. This specific result has been derived in [1,6]. Given this normalized auto-correlation function the channel signal decorrelation time  $\tau_0$  and coherence bandwidth  $f_0$  are defined by the relationships  $\rho''_{\tau}(0,0) = -2/\tau_0^2$  and  $\rho''_{\Delta f}(0,0) = -2/f_0^2$  where  $\rho''_{\tau}(0,0) = R''_{\tau}(0,0)/R(0,0)$  and  $\rho''_{\Delta f}(0,0) = R''_{\Delta f}(0,0)/R(0,0)$  denote the second derivatives of  $\rho(\tau, \Delta f)$  and  $R(\tau, \Delta f)$  with respect to  $\tau$  and  $\Delta f$ , respectively, evaluated at  $\tau = 0$  and  $\Delta f = 0$ . For the Rayleigh scintillation channel with  $R(\tau, \Delta f) = S_0 \rho(\tau, \Delta f)$ , we obtain the channel signal decorrelation time and coherence bandwidth

$$\tau_0 = \sqrt{2R(0,0)/|R''_{\tau}(0,0)|} = \tau_{01} \quad \text{Decorrelation Time} \quad (4a)$$

$$f_0 = \sqrt{2R(0,0)/|R''_{\Delta f}(0,0)|} = f_{01} \quad \text{Coherence Bandwidth} \quad (4b)$$

as one would expect. [Note that the second derivatives are always non-positive.]

The decorrelation time and coherence bandwidth of Rician ionospheric channel (1) can also be determined from the general expressions

$$\tau_0 = \sqrt{2R_1(0,0)/|R''_{1\tau}(0,0)|} = \tau_{01}/\sqrt{q+2\tau_{01}^2(\pi\delta f)^2} \quad (5a)$$

$$f_0 = \sqrt{2R_1(0,0)/|R''_{1\Delta f}(0,0)|} = f_{01}/\sqrt{q} \quad (5b)$$

We see that as the specular component becomes more significant ( $q = 1-p$  becomes smaller) both the decorrelation time and coherence bandwidth becomes larger.

For the terrestrial multipath channel we have the following expression for the signal auto-correlation function [1]

$$R_2(\tau, \Delta f) = S_0[\exp(i2\pi\delta f\tau) + m\rho_2(\tau, \Delta f)] \quad (6)$$

where  $S_0$  is the specular signal power and  $mS_0$  is the multipath (random) power for the total signal power ( $1+m$ ) $S_0 = R_2(\tau=0, \Delta f=0)$ . The normalized terrestrial multipath auto-

correlation function  $\rho_2(\tau, \Delta f)$  is taken to be [1]

$$\rho_2(\tau, \Delta f) = \exp(-i2\pi\Delta f\tau)[J_0(a)J_0(b) + 2\sum_{n=1}^{\infty}(-1)^n J_n(a)J_n(b)\cos\{n(\alpha_0 - \alpha_s)\}] \quad (7)$$

where  $a = 2\pi(v_0/\lambda)\tau\cos(\beta_0)$ ,  $b = 2\pi(\Delta f/f_c)(r_m/\lambda)\cos(\beta_s)$  that the angles define the unit direction vector  $u(\alpha_s, \beta_s) = [\cos(\alpha_s)\cos(\beta_s), \sin(\alpha_s)\cos(\beta_s), \sin(\beta_s)]$  towards the satellite as seen from the terminal and  $u(\alpha_0, \beta_0) = [\cos(\alpha_0)\cos(\beta_0), \sin(\alpha_0)\cos(\beta_0), \sin(\beta_0)]$  is the terminal multipath length,  $\lambda$  is the UHF wavelength,  $f_c$  is the UHF signal frequency,  $J_n$  is the Bessel function of the first kind of order  $n$ . The decorrelation time and coherence bandwidth corresponding to the auto-correlation function become

$$\tau_{02} = \sqrt{2/|\rho_{2\tau}''(0,0)|} = \lambda/[\pi v_0 \cos(\beta_0)] \quad (8a)$$

$$f_{02} = \sqrt{2/|\rho_{2\Delta f}''(0,0)|} = (c/\pi r_m)/\sqrt{2+\cos^2(\beta_s)} \quad (8b)$$

where  $c = f_c\lambda$  being the speed of light (300 m/ $\mu$ s). The decorrelation time and channel coherence bandwidth associated with the terrestrial channel

$$\tau_0 = \sqrt{2R_2(0,0)/|R_{2\tau}''(0,0)|} = \tau_{02}\sqrt{(1+m)/\{m+2\tau_{02}^2(\pi\delta f)^2\}} \quad (9a)$$

$$f_0 = \sqrt{2R_2(0,0)/|R_{2\Delta f}''(0,0)|} = f_{02}\sqrt{(1+m)} \quad (9b)$$

since in this case  $R_2(0,0) = (1+m)S_0$ .

The composite scintillation and terrestrial channel signal auto-correlation function can now be expressed as

$$R_3(\tau, \Delta f) = S_0[p + q\rho(\tau, \Delta f)][\exp(i2\pi\delta f\tau) + m\rho_2(\tau, \Delta f)] \quad (10)$$

where again the total power  $(1+m)S_0 = R_3(\tau=0, \Delta f=0)$  where specular power component is  $pS_0$  and the random power component is  $(1+m-p)S_0$ . The channel signal decorrelation time and channel coherence bandwidth can be solved from

$$\tau_0 = \sqrt{2R_2(0,0)/|R_{2\tau}''(0,0)|} = \sqrt{(1+m)/\{q/\tau_{01}^2 + m/\tau_{02}^2 + 2(\pi\delta f)^2\}} \quad (11a)$$

$$f_0 = \sqrt{2R_2(0,0)/|R_{2\Delta f}''(0,0)|} = \sqrt{(1+m)/\{q/f_{01}^2 + m/f_{02}^2\}} \quad (11b)$$

We see that when  $m = 0$  (no terrestrial multipath) we have the same result as (5a,b) and when the multipath is dominating as expected  $\tau_0 = \tau_{02}$  and  $f_0 = f_{02}$  as  $m \rightarrow \infty$ .

## RESULTS

We solve Eq. (10) numerically using a carrier frequency of  $f_c = 250$  MHz. For the ionospheric scintillation channel we take a decorrelation time of  $\tau_0 = 0.6$  sec and a coherence bandwidth of  $f_0 = 1$  MHz. For the terrestrial channel we take  $v_0 = 30$  mph, or 48.3 Km/hr, and  $r_m/\lambda = 100$ . Fig. 1 gives the normalized composite signal auto-correlation function as a function of time offset  $\tau$  for  $\Delta f = 0$ . We find, that for these channel parameters, the effective composite channel decorrelation time is larger than the ionospheric channel decorrelation time.




Fig. 1 Plot of normalized composite correlation function vs.  $\tau$  for  $\Delta f=0$ .

Fig. 2 shows the normalized composite signal auto-correlation function as a function of frequency offset  $\Delta f$  for  $\tau=0$ . We also find that the effective composite channel coherence bandwidth is larger than the ionospheric scintillation coherence bandwidth.




Fig. 2 Plot of normalized composite correlation function as a function of  $\Delta f$  for  $\tau=0$ .

### SUMMARY

We have developed a preliminary composite model for the combined effects of ionospheric scintillation and terrestrial multipath on a MUOS signal waveform. The composite model gives an effective decorrelation time and coherence bandwidth for the composite channel. We have found that the effective decorrelation time and coherence bandwidth of the composite channel can be different from the ionospheric channel parameters. In the future we will solve the composite model for a larger range of channel parameters.

### ACKNOWLEDGMENTS

We wish to acknowledge useful discussions with Norm Baumgarten and Keith Kumm. This work was supported by SPAWAR (PMW-146).



## REFERENCES

- [1] P. Kullstam, Rician and Rayleigh signal fading: ionospheric scintillation and terrestrial multipath channel characterization, Maxim Report, October 4, 2002.
- [2] M. Keskinen and P. Kullstam, An overall channel model including ionospheric scintillation and terrestrial multipath, *Proc. MILCOM 2002*, Anaheim, CA.
- [3] J.G. Proakis, *Digital Communications*, Third Ed., New York, McGraw Hill, 1995.
- [4] S. Ohmori, H. Wakana, and S. Kawase, *Mobile Satellite Communications*, Artech, Boston, 1998.
- [5] J. Parsons, *The Mobile Radio Propagation Channel*, John Wiley, New York, NY, 2000.
- [6] M.J. Keskinen and P. Kullstam. *Updated UHF Scintillation and Channel Parameters for MUOS*, NRL/PAIRCOM Memo Report, SPAWAR, March 2002.